

cells and to shift the condition bits in ShiftReg.

1.6 kill clock mode

kill clock mode (kill_clock_en = 1) that enables you to block propagation of fast_clock input to clock_out output. Asserting the kill_clock_en signal is effective in the two operating modes when the OCC is not active:

2. 结构伪代码

```
clock_mux21 tessent_persistent_cell_inject_tck_mux (
    .A0          ( slow_clock_buf_out
),
    .A1          ( ijtag_tck
),
    .S0          ( inject_tck
),
    .Y           ( slow_clock_tck_injected
)
);

cgand tessent_persistent_cell_cgc_fast_clock (
    .CK          ( fast_clock_buf_out
),
    .FE          ( fast_clock_en
),
    .TE          ( fast_clock_en
),
    .GCK         ( fast_clock_gated
)
);

cgand tessent_persistent_cell_cgc_slow_clock (
    .CK          ( slow_clock_tck_injected
),
    .FE          ( slow_clock_en
),
    .TE          ( slow_clock_en
),
    .GCK         ( slow_clock_gated
)
);

clock_mux21 tessent_persistent_cell_clock_out_mux (
    .A0          ( fast_clock_gated
```

```

),
    .A1                                ( slow_clock_gated
),
    .S0                                ( clock_mux_select
),
    .Y                                  ( clock_out
)
);

assign kill_clock_en_gated = kill_clock_en & ~test_mode;
assign fast_clock_en      = ((ShiftReg_SCAN_OUT & fast_capture_mode &
(SCAN_EN_inv_sync || active_upstream_parent_occ)) | (~test_mode)) &
(~kill_clock_en_gated);
assign slow_clock_en      = (((ShiftReg_SCAN_OUT & (~fast_capture_mode)) |
scan_en) & test_mode) | inject_tck | (shift_only_mode & scan_en);
assign clock_mux_select = ((scan_en | (~fast_capture_mode)) & test_mode)
| inject_tck | (shift_only_mode & scan_en);

```

3. Parent mode

Parent-mode operation is one of the operating modes of the standard OCC.

This operating mode bypasses the OCC clock gating logic and performs clock selection only. It requires a downstream child-mode OCC to perform the clock gating and chopping.

Parent-mode, 父OCC只做时钟function clk 与shift clk之间进行切换，不做OCC的pluse gateing(这部分由child-OCC来实现)

非SSN场景

top parent mode OCC + n个tile内部child OCC,无需单独shift clock连线到tile
tile内部也不用单独check shift timing

注意项：如果多个top parent mode OCC(频率不同) + tile child OCC, 因为function模式下不同频率时钟为异步关系，但是如果切换到shift模式下，全部都是shift时钟，它们之间是会存在skew的，需要插入latch

SSN场景

shfit clock都是走tile内部(由SSH产生)intest时不考虑tile与tile之间的shift clock skew差异，这时用标准OCC是最好的。

4. Child OCC

SSN好像是不支持child OCC

Child OCC有两种实现：

- 普通OCC的child mode
- child-only的OCC

```
# 级联OCC会报R27问题，配置成Parent OCC mode + child OCC mode就不会报这个问题。
add_core_instances -inst [get_inst top_rtl2_tessent_occ_parent_*] \
                    -parameter {parent_mode on fast_capture_mode on}
set_static_dft_signal_values retargeting3_mode 1
//set_drc_handling R27 warning
set_core_instance_parameters -instances \
    coreb_i1/coreb_rtl2_tessent_occ_clka_inst -parameter_values \
    {active_upstream_parent_occ on}
set_core_instance_parameters -instances \
    coreb_i1/coreb_rtl2_tessent_occ_clkb_inst -parameter_values \
    {active_upstream_parent_occ on}
set_core_instance_parameters -instances \
    coreb_i1/coreb_rtl2_tessent_occ_clkc_inst -parameter_values \
    {active_upstream_parent_occ on}
```

From:

<http://vmcc.vicp.net:9090/wiki/> - **wiki**

Permanent link:

http://vmcc.vicp.net:9090/wiki/doku.php?id=edastudy:tessent:tessent_occ&rev=1744703807

Last update: **2025/04/15 15:56**

