

# tessent集成vcs仿真

<https://blog.eetop.cn/blog-949909-6951555.html>

指定stdcell,io,memory等模块的仿真模型

```
set_simulation_library_source -f ./all_model.f
```

设置VCS安装目录

```
setenv VCS_HOME /tools/syn/vcs_mx-2022.6-SP1/
```

运行仿真命令指定仿真器是vcs

```
run_testbench_simulations
  -simulator vcs
  -compilation_options "+define+debussy"
  -simulator_options "-debug_access+all"
  -extra_verilog_files {../rtl/b.v ../rtl/c.v} # 可单独加入tessent 不能处理的文
件用于仿真, 比如一些加密文件
  -extra_top_modules module_name_list # 可用于设置一些额外共同task或force
  [-use_design_view_per_simulation on | off ] #设置是否用全文件, 不用v_interface
之类的; 开启后RTL会一些编译, 各自TB单独编译
```

另外需要说明的是如果是前仿真, 因为没有sdf的缘故出现时序违例的问题导致仿真不通过, 可以进入tessent自动生成的仿真目录修改vcs.simulation\_script在vcs命令添加nospecify或no\_notifier和notimgcheck

如果要dump fsdb波形, 在生成的vcs.simulation\_script文件中添加-debug\_access 修改TB文件, 在initial块中添加\$fsdbDumpvars(0,TB);

```
run_testbench_simulations
[-design_name design_name]
[-design_id design_id]
[-pattern_id pattern_id]
[-report_list]
[-select pattern_name_glob_list]
[-exclude pattern_name_glob_list]
[-generate_scripts_only | -run_only]
[-parallel_simulations {1 | 2...MAX_INT | maxcpu}]
[-expected_miscompare_count int]
[-simulation_id string]
[-simulator questa | vcs | incisive]
[-simulation_timeout time | unlimited]
[-keep_simulation_data on | off | on_failure]
[-store_simulation_waveforms on | off]
[-simulation_run_commands simulator_commands]
[-waveform_configuration_commands simulator_command_list]
[-compilation_macro_definitions {macro[=value] ... }]
```

```
[-simulation_macro_definitions {macro[=value] ... }]  
[-compilation_options option_list]  
[-simulator_options option_list]  
[-extra_verilog_files list_of_files] # 这可以单独加入tessent 不能处理的文件用于仿真, 比如一些加密文件  
[-extra_top_modules module_name_list]  
[-simulation_output_directory simulation_output_directory]  
[-simdut_output_directory simdut_output_directory]  
[-simdut_server] [-generate_simdut_files_only]  
[-use_design_view_per_simulation on | off ]  
[-no_wait]
```